

21W GALAXY LED - GALAXY 21 IP54 DECORATIVE ROUND BULKHEAD



CE 220-240V

These instructions should be read carefully and retained after installation for further reference and maintenance.

SAFETY

- Before installation, ensure that the mains supply to the luminaire is switched off and the circuit supply fuse is removed or MCB turned off.
- It is recommended that a qualified electrician is consulted or used for the installation of this luminaire and it is installed in accordance with the IEE wiring regulations.
- Check that the total load on the circuit, including this luminaire, does not exceed the rating of the circuit cable, fuse or MCB.

RATINGS

- This luminaire is of class II construction and does not require an earth connection.
- IP54 rated.
- F marked, suitable for installation on normal flammable surfaces.
- Ambient temperature: -20°C to 40°C.
- 220-240V AC rated.
- CE Approved.

INSTALLATION

- Remove the trim by twisting 45 degrees anti-clockwise and undo the 3 screws to release the diffuser. The screws are self retaining.
- The gear tray is hinged to allow easy access to the connections. Open the gear tray for access to the cable connections.
- Select a suitable cable entry point provided or by drilling into the base.
- Position and fix the base to a suitable solid surface using screws supplied.
- Enter supply cable into the luminaire ensuring that the hole is smooth or a grommet is fitted.
- Terminate the cable into the terminal block mounted on the underside of the gear tray ensuring correct polarity is observed any bare conductors are sleeved.
- Close the hinged gear tray.
- Re-fit the diffuser by screwing the 3 screws back into the base. Place the trim back on top and turn 45 degrees clockwise to lock in to place.

IMPORTANT – WHEN REPLACING OR FITTING THE LED GEAR TRAY ENSURE THE POWER IS SWITCHED OFF.