Installation Sheet L-GLK1 Additional RGB Smart Garden Light IP65 (Bluetooth



Please read these instructions before commencing installation & retain them for future reference.

Important information

It is recommended that the garden lights are installed by a qualified electrician ensuring the installation complies to current IEE wiring regulations & local building control. We will not accept responsibility for any claims arising from a poor installation.

Important User Advice

- For use with L-GLK4 RGB Smart Garden Light 4 set only
- This light operates at Safety Extra Low Voltage (24V), via a LED power supply.
- Never connect the light fittings directly to the mains.
- The garden lights are suitable for external use, but must not be submerged in water.
- Do not exceed the LED power supply load.

Installation Procedure

NOTE: The L-GLK1 additional light can only be installed as an intermediate lamp in the set.

- · Always switch off mains supply before servicing.
- Fix the garden lights in a suitable position.
- Each lamp has 2m of cable (1m on each side) with male and female connectors.
- Connect the 24V supply cable to the L-GLK4 power feed or adjacent lamps using the IP65 connectors:



- · You can add up to 2 additional lights to the L-GLK4 set.
- Turn ON power to test correct operation.

SPECIFICATIONS: • Input Voltage: DC 24V

• Power: 12W

• 2 metres cable

Lamp body material: ABS

• Colour Temperature: RGB

• Luminous Flux: 450-750lm

· Beam angle: 45-60 degrees

• IP Rating: IP65

Control Type: Bluetooth 4.0 Mesh

Bluetooth Range: up to 10m

• Working Temperature: -25°C~+40°C

2 Years Warranty

DIMENSIONS:



